

VK8302

Karaoke Amplifier

DESCRIPTION



FEATURES

- This is a Karaoke amplifier with excellent performance and multi-functions.
- Three Channel or two channel power output. Offer record output, line output, pre-output, bass output, middle channel output and line output.
- Three-way input for audio and video. sound resource is switchable in both automatically and manually.
- Five microphones input in 2 groups. The volume of each group can be adjusted separately, and each group provides +/- 12dB adjustment for treble, mediant, and bass.
- Music channel provides +/- 12dB adjustment for treble, and bass.
- Build in mic general volume, mic effect volume and music volume control knob.
- Build in music key changer function, S terminal control function.
- Build in L/R output, middle output volume control function.
- Sub channel has 80-250Hz adjustment function.
- Background Music(BGM) channel is in first priority, and it's available to adjust the input signal sensitivity.

TECHNICAL SPECIFICATIONS

Rated Power (RMS)	300W x 2(1kHz,8Ω)
THD (@1kHz)	0.02% (20Hz-20kHz,8Ω)
Frequency Response(-3dB)	20Hz-20kHz±1dB
Input Sensitivity/Impedance	MIC: 20mV/2kΩ Line: 200mV/10kΩ
Pitch Control	Music: LF(100Hz) ±12dB HF(10kHz) ±12dB MIC: LF(100Hz) ±12dB MF(1kHz) ±12dB HF(10kHz) ±12dB
Effect Type	Echo
Output Impedance	4-16Ω
Recommendatory Impedance	8Ω
Power Supply	220V,50Hz
Power Consumption	□1250W
Static Power Consumption	35W
Net Weight (1 pc)	13kg
Gross Weight (1 pc)	14.5kg
Dimension(W×D×H)	561 x 454 x 226 (mm)
