

# DA3300

Digital Karaoke Amplifier

## DESCRIPTION



## FEATURES

- 3-channel Music/Video Input, Automatic/Manual Sound Resource Switchable, 5 MIC Inputs in 2 Groups, Individual Volume Control etc.
- $\pm 8$  dB Treble, Mediant and Bass Control in Each Music Channel and MIC Channel.
- DSP technology, LCD screen, SCM production process.
- Have Mic volume knob, Mic effect volume knob and music volume knob. Each level can be shown in the LED display. MIC effect and music volume can be adjusted in L.R and center channel.
- Mute, Vocal Cancelation, Key Changer, Automatic singalong, S Terminal Line Control.
- Have Max Volume limitation and save current volume level function.

**TECHNICAL SPECIFICATIONS**

---

Output Power(1kHz,8Ω)	300W×3
THD (@1kHz)	<0.05% (20Hz-20kHz,8Ω)
Frequency Response(-3dB)	20Hz-20kHz±1dB
Input Sensitivity	Front Mic:20mV±10%/2KΩ Rear Mic:40mV±10%/2KΩ
Input Impedance	Line:200mV±10%/10KΩ Video:1Vp-p /75Ω ±8Ω
Tone Control	Music: Bass\Middle\Treble: 100Hz\1.6kHz\10kHz Mic: Bass\Middle\Treble:100Hz\1.6kHz\6.3kHz
Effect	ECHO/REV/ECHO+REV
Output Impedance	4-16Ω
Rated Impedance	8Ω
Power	AC~110-220V,50Hz/60Hz
Power Supply	220V-230V 50/60Hz, 1000VA
AC Power Outlets	Switched:200W Unsumption(2 Way):300W
Static Power Dissipation	30W
Net Weight (1 pc)	14.5kg
Gross Weight (1 pc)	15kg
Dimension(W×D×H)	507×422×202mm

---