

MU22

Digital Live Sound Console

DESCRIPTION

MU-22 rack mounted digital mixer is equipped with 16 channel mic / line in special voice amplifier with low distortion and low noise, with the maximum input capacity of + 24dbu (balanced). In each input, there are all band adjustable PEQ, HPF / LPF, comp and gate. Four high-quality digital effect processors (FX) are preset with effect parameters adjusted by professional tuners. In the output channel, PEQ and GEQ, voltage limit and delay are provided, and DCA and mute groups marshalling functions are also provided.

MU-22 digital mixer provides you with professional and smooth performance. The simple and powerful preset and scenes functions can easily save or call up the optimized parameter configuration. From now on, you can experience the relaxed and pleasant professional music.



FEATURES

- Input(22ch)
- 16-channels Mic / Line with full digital control gain analog pre-processing (XLR female plug and 1 / 4"TRS combinatorial input interface)
- 2 stereo Line-In channels
- 1 stereo USB Media channel(U disk playback or Bluetooth audio)
- Output(18ch)
- 8 channels AUX
- 4 channels MTRX
- 1 stereo channel Main L/R
- 1 stereo channel USB recording
- 1 stereo headphone channel
- 4 professional DSP effectors (FX)
- 8 DCA volume groups
- 4 MUTE groups

DATASHEET



Beta Three

TECHNICAL SPECIFICATIONS
